

How to assemble an  
edge-lit sign using a  
**Sign Lighting**  
**Australia**  
supplied lighting unit

# Sign Lighting Australia

- ◉ How to assemble an Edge Lit Sign with vinyl applied artwork



# Step #1

- ◉ Lightly sand all edges of the acrylic blade



## Step #2

- ◉ Flame / buff polish edge next to light source



## Step #3


- Apply black felt buffer at illuminated edge





# Step #4

- Drill 2 x holes (3.5mm diameter bit) for pins that will secure the acrylic blade inside the extrusion - centred from the polished edge -
- Std Extrusion:
  - - 28mm in
- Mini Extrusion:
  - - 14mm in
- Round Extrusion:
  - - 31mm in




# Step #5

- ◉ Strip safety sheet, remove adhesive residue with a vinyl prep solution to save time at final clean



# Step #6

- Apply any vinyl graphics in “reverse”






# Step #7

- Apply white vinyl around 3 edges of acrylic to reflect light source back into acrylic



# Step #8

- ◉ Insert blade into light fixture




# Sign Lighting Australia

- ◉ How to assemble an “ENGRAVED”  
Edge Lit Sign

# Step #1 - Engraved

- Prepare artwork, and cut or Laser etch in reverse on back side of acrylic



## Step #2 – “Engraved”

Complete all machining





# Step #3 – “Engraved”

- ◉ Engrave design



## Step #4 – “Engraved”

- ◉ Lightly sand all edges



## Step #5 – “Engraved”

- ◉ Flame / Buff polish edge next to light source



## Step #6 – “Engraved”


- Apply black buffer felt at illuminated edge





## Step #7 – “Engraved”

- Drill 2 x holes (3.5mm diameter bit) for pins that will secure the acrylic blade inside the extrusion centred from the polished edge –
- Std Extrusion:
  - - **28mm in**
- Mini Extrusion:
  - - **14mm in**
- Round Extrusion:
  - - **31mm in**






## Step #8 – “Engraved”

- ◉ Strip safety sheet, remove adhesive residue with a vinyl prep solution and clean with Sasign Acrylic Cleaner



## Step #9 – “Engraved”

- ◉ Apply white tape to unlit edges
- ◉ Insert Acrylic blade into lighting Unit



# CLEANING PRODUCTS

- ◉ Sasign acrylic polish – repairs
- ◉ DeSolvIt - removes adhesive residue



# Where to get more information

- ◉ Sign Lighting Australia
- ◉ 158 Lae Drive
- ◉ Coombabah, Qld 4216
- ◉ Tel: (07) 5564-9930
- ◉ Email:  
sales@signlighting.com.au
- ◉ [www.signlighting.com.au](http://www.signlighting.com.au)